


Tools Required:

- 2mm hex key
- Phillips medium screwdriver
- Adjustable wrench



Dimensions

- A: 4-3/4 "
- B: 5-1/8 "
- C: 5-1/2 "



Weight: 2.87 lbs.


Notice to Installer for 24 370:

1. See page 2 for specific product safety warnings.
2. Mounts directly to a standard octagonal 4" wiring box (by others) using mounting kit (provided).
3. Integral LED module and driver provided by BEGA within luminaire housing.
4. For downward orientation only.

24 370 - installation:

1. Loosen (2) 2mm hex screws and remove outer casting from luminaire base.
2. Feed luminaire wires through luminaire base and through adapter plate.
3. Make supply wiring and luminaire wiring connections in the wiring box:
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
Dimming (if applicable):
DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER DIM CONTROL WIRE
DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER DIM CONTROL WIRE
4. Mount luminaire base directly to recessed octagonal wiring box using mounting kit (included).
5. Place a small bead of silicone around the back side of the luminaire base that will come in contact with the finished wall (exterior applications only).
6. Replace outer casting and tighten (2) screws to secure, ensure the gasket is seated properly.

Figure 1: (Generic Image)



Relamping/Maintenance

No relamping required.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

Description	Part No
LED module (3000K)	LED-0650/830
LED module (4000K)	LED-0650/840
LED driver	75943

Lamp: 8.2W LED

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 90°C MIN.