Tools Required:

4mm hex key Adjustable wrench



Dimensions

A: 15-3/8 "

B: 19-5/16 "



Protection Class: IP65

Weight: 13.2 lbs.

Notice to Installer for 77 150:

- 1. See page 2 for specific product safety warnings.
- 2. For pole top applications only.
- 3. Slip fits 3" O.D. poles only.
- 4. LED module and integral driver provided by BEGA.
- 5. Pole top luminaire supplied with 25 feet of cable to route through pole.
- 6. Do NOT open the fixture.

77 150 - installation:

- 1. Route the luminaire wiring through to the pole base and slip luminaire over the top of the pole.
- 2. Secure luminaire by tightening set screws on pole fitter, evenly.
- 3. Make supply wiring connections to luminaire wires in pole base:

MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE

Dimming (if applicable):

DIMMING CONTROL WIRE (+) TO POSITIVE LUMINAIRE DIM CONTROL WIRE DIMMING CONTROL WIRE (-) TO NEGATIVE LUMINAIRE DIM CONTROL WIRE

Relamping/Maintenance

No relamping necessary.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable. **Replacement Parts**

Description

Outer diffuser LED driver

76053 LED Module (4K) LED-0554/840

LED-0553/840 LED-0554/830 LED Module (3K)

LED-0553/830

Part No

150434

Lamp: 16.8W LED Module

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

77 150



Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 90°C MIN.