


Tools Required:

4mm hex key
Adjustable wrench


Dimensions

A: 20-1/8 "

B: 26-1/8 "



Protection Class: IP65

Weight: 19.0 lbs.

Notice to Installer for 77 151:

1. See page 2 for specific product safety warnings.
2. For pole top applications only.
3. Slip fits 3" O.D. poles only.
4. LED module and integral driver provided by BEGA.
5. Pole top luminaire supplied with 25 feet of cable to route through pole.
6. Do NOT open the fixture.

77 151 - installation:

1. Route the luminaire wiring through to the pole base and slip luminaire over the top of the pole.
 2. Secure luminaire by tightening set screws on pole fitter, evenly.
 3. Make supply wiring connections to luminaire wires in pole base:
 - MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
 - NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
 - GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
- Dimming (if applicable):
- DIMMING CONTROL WIRE (+) TO POSITIVE LUMINAIRE DIM CONTROL WIRE
 - DIMMING CONTROL WIRE (-) TO NEGATIVE LUMINAIRE DIM CONTROL WIRE

Relamping/Maintenance

No relamping necessary.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

Description	Part No
Outer Diffuser	150413
LED Driver	75985-03
LED Module (4000K)	LED-0469/840
	LED-0472/840
LED Module (3000K)	LED-0469/830
	LED-0472/830

Lamp: 24W LED Module

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 90°C MIN.