


Tools Required:

- 4mm hex key
- Adjustable wrench



- Dimensions**
- A: 20-5/8 "
- B: 22-1/4 "



Weight: 21.38 lbs.

Notice to Installer for 84 120:

- 1. See page 2 for specific product safety warnings.
- 2. For pole top applications only.
- 3. Slip fits 3" O.D. poles only.
- 4. Pole inner dimension 2-3/8" MINIMUM.
- 5. LED module and integral driver provided by BEGA.
- 6. Pole top luminaire supplied with 35 feet of cable to route through pole.
- 7. Do NOT open the fixture.

84 120 - installation:

- 1. Route the luminaire wiring through to the pole base and slip luminaire over the top of the pole.
- 2. Secure luminaire by tightening (6) 4mm set screws on pole fitter, evenly.
- 3. Make supply wiring connections to luminaire wires in pole base:
 - MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
 - NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
 - GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
- Dimming (if applicable):
 - DIMMING CONTROL WIRE (+) TO POSITIVE LUMINAIRE DIM CONTROL WIRE
 - DIMMING CONTROL WIRE (-) TO NEGATIVE LUMINAIRE DIM CONTROL WIRE

Relamping/Maintenance
No relamping necessary.

Accessories
Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts	
Description	Part No
LED Driver	75985-01
LED Module (4000K)	(x8) LED-0412/840
LED Module (3000K)	(x8) LED-0412/830

Lamp: 24W LED Module

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 90°C MIN.