
Tools Required:

4mm hex key



Dimensions

A: 28 "

14-1/4 "



Protection Class: IP65

Weight: 32.2 lbs.

Notice to Installer for 84 403:

- 1. See page 2 for specific product safety warnings.
- 2. For pole top applications only.
- 3. Slip fits 3" O.D. poles only.
- 4. Requires a MINIMUM 2-1/2" length of straight diameter pole/tenon.
- 5. LED module and integral driver provided by BEGA.
- 6. Pole top luminaire supplied with 25 feet of cable to route through pole.
- 7. Fixture should not be opened during installation.

84 403 - installation:


- 1. Lead luminaire wires into top of pole and through to the base.
- 2. Slip luminaire onto top of pole and secure by tightening (4) M8 set screws on pole, evenly.
- 3. Make supply wiring and luminaire wiring connections inside pole base:

MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE

Dimming (if applicable):

DIMMING CONTROL WIRE (+) TO POSITIVE LUMINAIRE DIM CONTROL WIRE DIMMING CONTROL WIRE (-) TO NEGATIVE LUMINAIRE DIM CONTROL WIRE

Figure 1



Relamping/Maintenance

No relamping necessary.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable. **Replacement Parts**

Description

Part No

LED Driver

75985-01 LED Module (3000K) (x2) LED-0403/830

LED Module (4000K) (x2) LED-0403/840

23.6W LED Module Lamp:



Product Safety Warnings:

MIN 60°C SUPPLY CONDUCTORS.

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

LES FILS D'ALIMENTATION 60°C MIN.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.