


**Tools Required:**

- 3mm hex head screwdriver
- Phillips medium screwdriver

**Dimensions**

- A:** 12-5/8"
- B:** 4-1/8"
- C:** 7-1/4"



**Protection Class:** IP65

**Weight:** 5.8 lbs.

**Notice to Installer for 24 361:**

1. See page 2 for specific product safety warnings.
2. Mounts directly to finished surface over standard recessed single gang box (by others)
3. In conformance with UL Standard 1598, a silicone based sealant must be used between luminaire and supporting wall.
4. Integral LED module and LED driver supplied by BEGA.

**24 361 - installation:**

1. Loosen (2) 3mm hex head set screws at luminaire canopy and remove luminaire mounting plate.
2. Feed luminaire wires through luminaire base.
3. Make supply wiring and luminaire wiring connections in the octagonal wiring box:  
 MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE  
 NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE  
 GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE

**Dimming (if applicable):**

- DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER WIRE
- DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER WIRE

4. Place a small bead of silicone around the back side of the mounting base and luminaire that will come in contact with the finished wall (exterior applications only).
5. Mount mounting plate to wall over standard recessed single gang box using hardware by others.
6. Mount luminaire to mounting plate and tighten (2) 3mm hex head set screws to secure luminaire.

**Relamping/Maintenance**

No relamping necessary.

**Accessories**

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

**Replacement Parts**

Description	Part No
Faceplate Assembly	FP24361
LED driver (120-277V)	75934
LED Module (3000K)	LED-0609/930
LED Module (4000K)	LED-0609/940

**Lamp:** 33.6W LED

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

**Product Safety Warnings:**

**THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.**

**MIN 60°C SUPPLY CONDUCTORS.**

**CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.**

**LES FILS D'ALIMENTATION 60°C MIN.**