


Tools Required:

4mm hex key
5mm hex key
Flat head screw driver medium
Phillips head screw driver medium


Dimensions

A: 4-1/4 x 6-1/2 "
B: 27-5/8 "
C: 2 "
D: 7-1/2 x 3-1/2 "


Protection Class: IP65

Weight: 7.7 lbs

Notice to Installer for 77 551:

1. This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.
2. Mounts directly over a standard, vertical single gang wiring box (by others).
3. Ceiling and wall applications only.
4. In conformance with U.L. Standards 1598, a silicone-based sealant **MUST** be used between the mounting plate edge and supporting wall.
5. **WARNING:** LEDs are high quality electrical components. Please avoid touching them directly during installation.

77 551 - installation:

1. Loosen the (4) 4mm hex screw on the luminaire canopy and remove luminaire base from luminaire.
2. Feed luminaire wiring through the luminaire base and mounting plate.
3. Make supply wiring and luminaire wiring connections inside the wiring box:
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
Dimming (if applicable):
DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER DIM CONTROL WIRE
DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER DIM CONTROL WIRE
4. Mount luminaire to ceiling or wall using hardware (by others). Minimum size: 8-32 screws
5. Replace luminaire canopy (with luminaire attached) and tighten (4) 4mm screws.
8. To adjust head angle, use 5mm hex key to loosen adjustment screw. Adjust luminaire head as needed and tighten adjustment screw.

Relamping/Maintenance

No relamping necessary.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Shield

70 500

Replacement Parts

Description	Part No
-------------	---------

Lens	140966
Gasket	831372

LED driver	75940
LED module (3000K)	LED-0313/930
LED module (4000K)	LED-0313/940

Lamp: 17.9W LED