

Tools Required:


- 3mm hex key
- 4mm hex key
- Adjustable wrench



UL listed, suitable for wet locations.

Protection Class: IP65

Weight: 25.3 lbs.



Dimensions

A: 27-1/2 "

B: 12-5/8 "



Notice to Installer for 88 263:

1. For pole top applications only.
2. Slip fits 3" O.D. poles only.
3. LED module and integral driver provided by BEGA.
4. Pole top luminaire supplied with 25 feet of cable to route through pole.

88 263 - installation:

1. Route the luminaire wiring through to the pole base and slip luminaire over the top of the pole.
2. Secure luminaire by tightening set screws on pole fitter.
3. Make supply wiring connections to luminaire wires in pole base:
 - MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
 - NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
 - GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE

Dimming (if applicable):

- DIMMING CONTROL WIRE (+) TO POSITIVE LUMINAIRE DIM CONTROL WIRE
- DIMMING CONTROL WIRE (-) TO NEGATIVE LUMINAIRE DIM CONTROL WIRE

Relamping/Maintenance

NO relamping necessary.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

<u>Description</u>	<u>Part No</u>
Lens	150347
Lens gasket	830810
LED driver (120-277V)	76027

Lamp: 25.2W LED