


**Tools Required:**

- 5mm Hex key
- 6mm Hex key
- 8mm Hex key

**Overview:**

LED Watts: 35.7 W  
 System Watts: 39.7 W  
 Controllability: 0-10V, TRIAC, and ELV dimming to 1%  
 Weight: 33.0 lbs.  
 Protection Class: IP65


**Dimensions**

**A:** 31-1/2"

**B:** 21-1/4"


**Notice to Installer:**

1. Do not open luminaire.
2. For pole top applications only.
3. Slip fits 3" O.D. pole top or tenon.
4. Luminaire requires at least 3-1/2" of straight diameter pole or tenon.
5. LEDs are high-quality electronic components! Please avoid touching diode of LED module when installing.

**Pole top reflector assembly:**

1. Loosen the (2) 8mm hex screws at the top of the support rods and remove screws and fixing plates.
2. Attach the reflector disk to the support rods by positioning the joint shells over the joint bearings. Make sure the drip edges are oriented downwards.
3. Replace the fixing plates and screws.
4. Tilt the reflector to the desired orientation (0-30 degrees).
5. Tighten the (2) 8mm hex screws to secure in place.

**98 019 Installation:**

1. Route luminaire wiring down to base of pole.
2. Make supply wiring connections:  
 MAIN VOLTAGE SUPPLY WIRE TO BLACK WIRE  
 NEUTRAL (COMMON) SUPPLY WIRE TO WHITE WIRE  
 GREEN GROUND SUPPLY WIRE TO GREEN WIRE  
 Dimming (if applicable):  
 DIMMING CONTROL SUPPLY WIRE (+) TO POSITIVE DRIVER DIM CONTROL WIRE  
 DIMMING CONTROL SUPPLY WIRE (-) TO NEGATIVE DRIVER DIM CONTROL WIRE
4. Slip luminaire over the top of the pole.
5. Tighten the (6) 5mm set screws evenly to secure to pole.

**Accessories**

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

**Maintenance:**

Clean regularly with solvent-free cleaner removing dirt and debris. Do not use high pressure cleaners.

**Replacement Parts**

See label inside of fixture for LED replacement part number.

Consult factory for all other replacement components.

**Product Safety Warnings:**

**THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS. MIN 90°C SUPPLY CONDUCTORS.**

**CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.**

**LES FILS D'ALIMENTATION 90°C MIN.**